

Operating System v1.2 for RS7000

These is the latest operating system available for the RS7000 Music Production Studio. Please review the followings to install the latest operating system.

Tools required for update

You will need the following...

8MB or larger SmartMedia (3.3V)

SmartMedia floppy disk adaptor

How to update

1. Insert the SmartMedia containing the upgrade program into the slot on the front panel of RS7000. The correct direction of SmartMedia is printed on the panel.
2. Turn the power on with "REC" button and "STOP" button pressed and held.
3. Press "ENTER" button after version check. The program is automatically updated and the process is displayed on LCD.
4. If the program successfully updated, the message shown in appears to prompt to reboot the system. Turn the power off.
5. Remove the SmartMedia from the slot.
6. "Factory Set" is performed.

Turn the power on with "OCT DOWN" button and "OCT UP" button and "STORE" button pressed and held. The data is set to the factory default settings.

Important Notice

This update is to be performed at your own risk. If by any chance an accident should occur during the update process, such as a power failure or a mistake in the update procedure, the unit may not function properly afterwards.

Yamaha Corporation shall not be held liable for any losses or damages (including, but not limited to, loss of profit, data or any other monetary loss) resulting from the use or misuse of this software update, even if Yamaha Corporation has informed the user beforehand of the possibility of such damages.

Posting this update on a network, putting it on a CD-ROM or other medium for sale or inclusion in a magazine, or altering it in any way is prohibited without the permission of Yamaha Corporation.

All trademarks and registered trademarks used herein are property of their respective holders.

(C) Copyright 2002 YAMAHA CORPORATION

All Rights Reserved